


SPA100

Amorphorus 12V 1.5W 100mA SOLAR PANEL

Fitted with a 3m lead and cigarette lighter plug that features a built in flashing L.E.D to show that the panel is producing power.



FEATURES

Discharge Protection

Includes a Smart Control unit to prevent solar discharge at night.

Maintains Your Battery

Can be used on larger batteries to prevent power drain caused by radio memories, clocks, alarms and onboard computers.

Easy To Use

Easy connection using the cigarette lighter plug. For non-vehicle applications where a cigarette lighter socket is unavailable, purchase Projecta cigarette lighter adaptor, CLE1006.

SPECIFICATIONS

PART NO.	SPA100
TYPE	Amorphorus
RATED POWER	1.5W at 1000W/m ² , 25°C
SHORT CIRCUIT CURRENT	115mA
PEAK POWER	13–15V (90–105mA)


BATTERY CHARGE TIMES

SPA100	VOLTAGE	BATTERY SIZE	CHARGE TIME
AUTOMOTIVE	12V	100–550CCA	Maintenance
MARINE	12V	150–600MCA	Maintenance
DEEP CYCLE	12V	7–40Ah	Maintenance

SPA400

Amorphorus 12V 5W 400mA SOLAR PANEL

Fitted with a 2m lead and battery clips.



FEATURES

Discharge Protection

Includes a Smart Control unit to prevent solar discharge at night.

Maintains Your Battery

Can be used on larger batteries to prevent power drain caused by radio memories, clocks, alarms and onboard computers.

Extend Your Running Time

Use the solar panel to extend the running time of your battery. Connect the panel to the battery and use the battery as normal to power your appliances.

SPECIFICATIONS

PART NO.	SPA400
TYPE	Amorphorus
RATED POWER	5W at 1000W/m ² , 25°C
SHORT CIRCUIT CURRENT	500mA
PEAK POWER	13–16.5V (340–400mA)

BATTERY CHARGE TIMES

SPA400	VOLTAGE	BATTERY SIZE	CHARGE TIME
AUTOMOTIVE	12V	150–650CCA	Maintenance
MARINE	12V	200–700MCA	Maintenance
DEEP CYCLE	12V	17–55Ah	Maintenance